

## Serviceable Single-Gas Detector

The next-generation single-gas detector that helps you reduce cost, ensure compliance and know your workers are protected.

Honeywell BW<sup>™</sup> Solo has everything you expect – plus additional features to make your compliance easier and more cost-effective than ever. All with a reliable life span, one-button operation and small, lightweight profile. Honeywell BW™ Solo is:

- The easiest single-gas detector to service, with no need to take it apart to replace sensors, batteries and sensor filters. That means long life and low cost.
- Complete with an extensive selection of sensor options. Count on comprehensive detection, whether you're monitoring for common or exotic hazards.
- The first single-gas detector with the 1-Series sensor for CO, H<sub>2</sub>S, O<sub>2</sub> and CO<sub>2</sub>. That means high accuracy, lower costs and faster sensor response time for the gases you monitor most often.
- Compatible with IntelliDoX. Save time and centralize data with automated bump testing, calibration and instrument management. Use IntelliDoX docking stations with Honeywell SafetySuite Device Configurator software to maintain and monitor your entire fleet from practically anywhere.



Easy to handle



## FEATURES AND BENEFITS

### For even more time-saving convenience - plus remote visibility on alarms choose the wireless version. And manage it from your smartphone.


Pair the wireless Honeywell BW™ Solo with our Safety Communicator mobile app and detector readings are sent instantly to Honeywell's real-time monitoring software – Honeywell Safety Suite Real Time – which can be accessed from any device with an internet connection, and get remote visibility on worker safety and location.

You can also use the wireless Honeywell BW™ Solo to share gas data with the desktop software - no dock required.

### Other Honeywell BW<sup>™</sup> Solo features:

- Option to activate IntelliFlash™ or non-compliance flash
- Ability to assign detectors to workers and locations
- Easy-to-read display for multiple languages
- Data logging with rolling 24-hour peak reading





	BW <sup>™</sup> SOLO & BW <sup>™</sup> SOLO WIRELESS	BW™ SOLO LITE*
SENSOR TYPE	1-Series and 4-Series	4-Series only
DATALOGGING	Yes	-
EVENTLOGGING	50 Events	5 Events
LANGUAGES SUPPORTED	11	5
WORKER & LOCATION ASSIGNMENT	Yes	-

\*Not available in North America.



# Honeywell BW<sup>TM</sup> Solo Technical Specifications

TECHNICAL SPECIFICATIONS         SIZE       7.0 × 6.7 × 3.6 cm (2.7 × 2.6 × 1.4 in) (1-Series sensor models)         7.0 × 6.7 × 4.1 cm (2.7 × 2.6 × 1.4 in) (4-Series sensor models)         WEIGHT       103 to 116 g (3.6 to 4.1 oz), depending on installed sensor         HUMIDITY       0% - 95% RH (non-condensing)         INGRESS       IP66/68         PROTECTION       IP66/68         SELF-TEST       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY       12 months (6 months for 1-Series 0 <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> LIFE       • Bluetooth <sup>w</sup> Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Change High, Low, TWA and STEL alarm setpoints       • Latching alarms       • Latching alarms         • Latching alarms       • Enable IntelliFlash and non-compliance indicators       • German, Italian, Russian, Japanese, Chinese, And Korean only)         CERTIFICATIONS       Image: Class I, Division 1, Groups A, B, C, D T4       Class I, Zone 0, AEx/Ex ia IIC T4 Ga - 40°Cs Tamb ≤ 60°C         AND APPROVALS       IECEx: IECEX SIR 18.0058       Ex ia IIC T4 Ga (Se) II Ma =40°Cs Tamb ≤ 60°C         IECE: IECEX SIR 18.0058       Ex ia IIC T4 Ga / Ex ia IIMa =40°Cs Tamb ≤ 60°C       FC CID: SU3BWS1		ATIONS		
TOX7.0 x 6.7 x 4.1 cm (2.7 x 2.6 x 1.6 in) (4-Series sensor models)WEIGHT103 to 116 g (3.6 to 4.1 oz), depending on installed sensorHUMIDITY0% - 95% RH (non-condensing)INGRESS PROTECTIONIP66/68ALARMS AND TYPEVisual, vibrating, audible (95 dB); Low, High, TWA, STEL, non-complianceSELF-TESTSensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)TYPICAL BATTERY LIFE12 months (6 months for 1-Series O_2), 2 months for 1S CO2CONNECTED• Bluetooth <sup>™</sup> Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator AppUSER OPTIONS• Reset TWA, STEL and Peak readings • Change High, Low, TWA and STEL alarm setpoints • Latching alarms • Enable IntelliFlash and non-compliance indicators • Set calibration and/or bump test reminders• Assign worker and location assignments • Language select: English, Russian, Japanese, Chinese, and Korean only)CERTIFICATIONS AND APPROVALSIf :< Class I, Division 1, Groups A, B, C, D T4 Class I, Zone O, AEX/Exia IIC T4 Ga -40°Cs Tamb s 60°C IECE: IECE: SIR 18.0058 Exia IIC T4 Ga / Exia IIC T4 Ga (E) IM1 Exia I Ma -40°Cs Tamb s 60°CIECE: IECE: ICC ID: SU38WS1 IC: IC: 20969-BWS1 RED: RED: RED: RED: RED Directive 2014/53/EUMar A9°Cs Tamb s 60°C For additional certifications, please review the manual or consult Honeywell Analytics.WARRANTY3 years for 1-Series detectors and sensors (H_2S, CO, O_2, CO2) 2 years for 4-Series detectors and sensors				
HUMIDITY       0% - 95% RH (non-condensing)         INGRESS PROTECTION       IP66/68         ALARMS AND TYPE       Visual, vibrating, audible (95 dB); Low, High, TWA, STEL, non-compliance         SELF-TEST       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> CONNECTED       • Bluetooth™ Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Change High, Low, TWA and STEL alarm setpoints       • Latching alarms       • Language select: English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Nortenan, Portuguese, Dutch (Honeywell BW™ Solo Lite*: bump test reminders         • Set calibration and/or bump test reminders       Class I, Division 1, Groups A, B, C, D T4 Class I, Zone 0, AEx/Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         ATEX:       Sira 18ATEX2243       Cf 2460 @II 1G Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         IECEx:       IECEx SIR 18.0058       Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         IECEX:       IECEX SIR 18.0058       Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         IECEX:       IECEX SIR 18.0058       Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         IECEX:       IECEX SIR 18.0058       Ex ia IIC T4 Ga -40°Cs Tamb ≤ 60°C         IEC	SIZE			
INGRESS PROTECTION       IP66/68         ALARMS AND TYPE       Visual, vibrating, audible (95 dB); Low, High, TWA, STEL, non-compliance         SELF-TEST       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> CONNECTED WORKER       • Bluetooth™ Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Lanching alarms       • Language select: English, French, Spanish, Enable IntelliFlash and non-compliance indicators       • Language select: English, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS AND APPROVALS       Iff:       Class I, Division 1, Groups A, B, C, D T4 Class I, Zone 0, AEx/Ex ia IIC T4 Ga -40°C≤ Tamb ≤ 60°C         IECEX:       IECEX: SIR 18.0058 Ex ia IIC T4 Ga -40°C≤ Tamb ≤ 60°C       IECEX: IECEX SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IC:       20969-BWS1 RED:       RE-D Directive 2014/53/EU For additional certifications, please review the manual or consult Honeywell Analytics.         WARRANTY       3 years for 1-Series detectors and sensors (H <sub>2</sub> S, CO, O <sub>2</sub> , CO <sub>2</sub> ) 2 years for 4-Series detectors and sensors	WEIGHT	103 to 116 g (3.6 to 4.1 oz), depending on installed sensor		
PROTECTION       ALARMS AND TYPE       Visual, vibrating, audible (95 dB); Low, High, TWA, STEL, non-compliance         SELF-TEST       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> LIFE       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> CONNECTED       • Bluetooth™ Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Language select:       and STEL alarm setpoints       • Language select:         • Language select:       English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Notch (Honeywell BW™ Solo Lite*: bump test reminders         • Set calibration and/or bump test reminders       • Charge High, Low, TWA (Lass I, Zone O, AEx/Ex ia IIC T4 Ga -40°Cs Tamb s 60°C         AND APPROVALS       Image: Class I, Division 1, Groups A, B, C, D T4 (Lass I, IM = 40°Cs Tamb s 60°C         IECEx:       IECEx SIR 18.0058 (Class I, IC T4 Ga / Class I, IC T4 Ga / Ex ia IIC T4 Ga / Class I, IC T4 Ga / Ex ia IIC T4 Ga / Ex ia IIC T4 Ga / Class I, IC T4 Ga / Class I, IC T4 Ga / Class I, IC T2 O969-BWS1 <th>HUMIDITY</th> <th>0% - 95% RH (non-condensing)</th>	HUMIDITY	0% - 95% RH (non-condensing)		
SELF-TEST       Sensor integrity, circuitry, battery and audible/visual alarms on activation; battery (continuous)         TYPICAL BATTERY LIFE       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> CONNECTED WORKER       • Bluetooth™ Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Change High, Low, TWA and STEL alarm setpoints       • Language select: English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Norean, Portuguese, Dutch (Honeywell BW <sup>™</sup> Solo Lite*: English, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS AND APPROVALS       Image: Class I, Division 1, Groups A, B, C, D T4 Class I, Zone O, AEX/Exia IIC T4 Ga German, Italian, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS END		IP66/68		
on activation; battery (continuous)         TYPICAL BATTERY LIFE       12 months (6 months for 1-Series O <sub>2</sub> ), 2 months for 1S CO <sub>2</sub> CONNECTED WORKER       • Bluetooth <sup>™</sup> Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Change High, Low, TWA and STEL alarm setpoints       • Assign worker, and location assignments         • Latching alarms       • Enable IntelliFlash and non-compliance indicators       • Dortuguese, Dutch (Honeywell BW <sup>™</sup> Solo Lite*: English, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS AND APPROVALS       Image: Class I, Division 1, Groups A, B, C, D T4 Class I, Zone 0, AEX/Exia IIC T4 Ga -40°C≤ Tamb ≤ 60°C         IECEx:       IECEx SIR 18A058 Ex ia IIC T4 Ga / 40°C≤ Tamb ≤ 60°C         IECEx:       IECEX: IECEX SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IECEx:       IECEX SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IECE:       20969-BWS1 RED:       RED:         RED:       RE-D Directive 2014/53/EU For additional certifications, please review the manual or consult Honeywell Analytics.         WARRANTY       3 years for 1-Series detectors and sensors (H <sub>2</sub> S, CO, O <sub>2</sub> , CO <sub>2</sub> ) 2 years for 4-Series detectors and sensors	ALARMS AND TYPE			
LIFE       • Bluetooth™ Low Energy (BLE) – Ability to connect to the Honeywell Safety Communicator App         USER OPTIONS       • Reset TWA, STEL and Peak readings       • Assign worker and location assignments         • Change High, Low, TWA and STEL alarm setpoints       • Latching alarms       • Language select: English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Korean, Portuguese, Dutch (Honeywell BW™ Solo Lite*: English, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS AND APPROVALS       Image: Sign Sign Sign Sign Sign Sign Sign Sign	SELF-TEST			
WORKERto the Honeywell Safety Communicator AppUSER OPTIONS• Reset TWA, STEL and Peak readings • Change High, Low, TWA and STEL alarm setpoints • Latching alarms • Enable IntelliFlash and non-compliance indicators • Set calibration and/or bump test reminders• Assign worker and location assignments • Language select: English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Korean, Portuguese, Dutch (Honeywell BW <sup>™</sup> Solo Lite*: English, Russian, Japanese, Chinese and Korean only)CERTIFICATIONS AND APPROVALSImage: Class I, Division 1, Groups A, B, C, D T4 Class I, Zone 0, AEx/Ex ia IIC T4 Ga -40°C≤ Tamb ≤ 60°CATEX:Sira 18ATEX2243 Cf 2460 @VII 1G Ex ia IIC T4 Ga @VI M1 Ex ia I Ma -40°C≤ Tamb ≤ 60°CIECEx:IECEx SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°CIECEx:IECEx SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°CIECEx:RED:RE-D Directive 2014/53/EU For additional certifications, please review the manual or consult Honeywell Analytics.WARRANTY3 years for 1-Series detectors and sensors (H <sub>2</sub> S, Co, O <sub>2</sub> , CO <sub>2</sub> ) 2 years for 4-Series detectors and sensors		12 months (6 months for 1-Series $\rm O_2$ ), 2 months for 1S $\rm CO_2$		
Peak readings       Iocation assignments         Change High, Low, TWA and STEL alarm setpoints       Iocation assignments         Latching alarms       Enable IntelliFlash and non-compliance indicators       Iocation assignments         Set calibration and/or bump test reminders       Korean, Portuguese, Dutch (Honeywell BW <sup>™</sup> Solo Lite*: English, Russian, Japanese, Chinese and Korean only)         CERTIFICATIONS AND APPROVALS       Image: Class I, Division 1, Groups A, B, C, D T4 Class I, Zone 0, AEx/Ex ia IIC T4 Ga -40°C≤ Tamb ≤ 60°C         ATEX:       Sira 18ATEX2243 C€ 2460 (m) I 1G Ex ia IIC T4 Ga (m) 11 Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IECEx:       IECEx SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IECEx:       IECEx SIR 18.0058 Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°C         IECE ID:       SU3BWS1 IC:       20969-BWS1 RED:         RED:       RE-D Directive 2014/53/EU For additional certifications, please review the manual or consult Honeywell Analytics.         WARRANTY       3 years for 1-Series detectors and sensors (H <sub>2</sub> S, CO, O <sub>2</sub> , CO <sub>2</sub> ) 2 years for 4-Series detectors and sensors				
AND APPROVALS $\bigcirc 1^{\circ}$ $> 1^{\circ}$	USER OPTIONS	<ul> <li>Peak readings</li> <li>Change High, Low, TWA and STEL alarm setpoints</li> <li>Latching alarms</li> <li>Enable IntelliFlash and non-compliance indicators</li> <li>Set calibration and/or bump test reminders</li> <li>Location assignments</li> <li>Language select: English, French, Spanish, German, Italian, Russian, Japanese, Chinese, Korean, Portuguese, Dutch (Honeywell BW<sup>™</sup> Solo Lite* English, Russian, Japanese</li> </ul>		
2 years for 4-Series detectors and sensors		Class I, Zone O, AEx/Ex ia IIC T4 Ga -40°C≤ Tamb ≤ 60°CATEX:Sira 18ATEX2243C€ 2460 ( $\textcircled{M}$ )I 1G Ex ia IIC T4 Ga( $\textcircled{M}$ )I M1 Ex ia I Ma -40°C≤ Tamb ≤ 60°CIECEx:IECEx SIR 18.0058Ex ia IIC T4 Ga / Ex ia I Ma -40°C≤ Tamb ≤ 60°CFCC ID:SU3BWS1IC:20969-BWS1RED:RE-D Directive 2014/53/EUFor additional certifications, please review the manual or		
	WARRANTY	3 years for 1-Series detectors and sensors ( $H_2S$ , $CO$ , $O_2$ , $CO_2$ ) 2 years for 4-Series detectors and sensors		

DUE TO ONGOING RESEARCH AND PRODUCT IMPROVEMENT, SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE.



### **INTELLIDOX DOCKING SYSTEM**

IntelliDoX combines smart-docking modules with our instrument management system to provide automated testing and record keeping.

### For more information

www.safety.honeywell.com

### Honeywell Gas Analysis and Safety

9680 Old Bailes Rd, Fort Mill, SC 29707 (803) 835-8000

#### **Contact us**

US:	Canada:
Tel. 800.430.5490	Tel. 888.2
Fax. 800.322.1330	Fax. 888.

212.7233 .667.8477

informationsp@honeywell.com

GAS\_Honeywell BW Solo\_DS | Rev B | 12/20 © 2020 Honeywell International Inc.

SENSOR SPECIFICATIONS				
GASES	STANDARD MEASURING RANGE	RESOLUTION	OPERATING TEMPERATURE	
H <sub>2</sub> S (1S)	0-200 ppm	0.1 ppm	-40°C to +60°C (-40°F to +140°F)	
CO (1S)	0-2000 ppm	1 ppm	-40°C to +60°C (-40°F to +140°F)	
CO <sub>2</sub> (1S)	0-50,000 ppm certification pending	100 ppm	-20°C to +60°C (-4°F to +140°F)	
0 <sub>2</sub> (1S)	0-30% v/v	0.1% v/v	-40°C to +60°C (-40°F to +140°F)	
Cl <sub>2</sub> (4S)	0-50 ppm	0.1 ppm	-20°C to +40°C (-4°F to +104°F)	
ClO <sub>2</sub> (4S)	0-1 ppm	0.01 ppm	-20°C to +40°C (-4°F to +104°F)	
CO-H (4S)	0-2000 ppm	0.5 ppm	-30°C to +50°C (-22°F to +122°F)	
ETO (4S)	0-100 ppm	0.1 ppm	-30°C to +50°C (-22°F to +122°F)	
H <sub>2</sub> (4S)	0-1000 ppm	2 ppm	-20°C to +50° (-4°F to +122°F)	
H <sub>2</sub> S (EXT. RANGE) (4S)	0-500 ppm	0.1 ppm	-40°C to +50°C (-40°F to +122°F)	
HCN (4S)	0-100 ppm	0.1 ppm	-20°C to +50°C (-4°F to +122°F)	
NH <sub>3</sub> (4S)	0-100 ppm	1 ppm	-20°C to +40°C (-4°F to +104°F)	
NH <sub>3</sub> (EXT. RANGE) (4S)	0-1000 ppm	1 ppm	-20°C to +40°C (-4°F to +104°F)	
NO (4S)	0-250 ppm	0.2 ppm	-30°C to +50°C (-22°F to +122°F)	
NO <sub>2</sub> (4S)	0-100 ppm	0.1 ppm	-20°C to +50°C (-4°F to +122°F)	
0 <sub>3</sub> (4S)	0-1 ppm	0.01 ppm	-20°C to +40°C (-4°F to +104°F)	
PH <sub>3</sub> (4S)	0-5 ppm	0.1 ppm	-20°C to +50°C (-4°F to +122°F)	
SO <sub>2</sub> (4S)	0-100 ppm	0.1 ppm	-40°C to +50°C (-40°F to +122°F)	
H <sub>2</sub> S (4S)*	0-100 ppm	0.1 ppm	-20°C to +50°C (-4°F to +122°F)	
CO (4S)*	0-1000 ppm	1 ppm	-20°C to +50°C (-4°F to +122°F)	
0 <sub>2</sub> (4S)*	0-30% v/v	0.1% v/v	-20°C to +50°C (-4°F to +122°F)	

1S = 1-Series sensor / 4S = 4-Series sensor

\*Honeywell BW™ Solo Lite only (not available in North America)



Representantes / Distribuidores Autorizados	THE
💳 Argentina	FUTURE
Tel: (+54 11) 5352 2500	IS
Email: info@dastecsrl.com.ar	WHAT
Web: www.dastecsrl.com.ar	WE
🔚 Uruguay www.dastecsrl.com.uy	MAKE IT

